

ON Semiconductor®



APPLICATION NOTE AND9316/D

AX5043

Sending FM tones (ZVEI)

Revision 2



Table of Contents

1. Introduction.....	3
2. The AX5043_TX_FM_tones_(ZVEI) Project.....	4
2.1. Routines.....	4
void init_ax5043(void).....	4
void send_tone_prepare(void)	5
void send_tone(uint8_t n).....	5
void send_tone_end()	5
void timer0_interrupt(void)	5
2.2. Variables	6
uint8_t freq_tbl_sin[256][4].....	6
uint8_t tone_rclk_div	6
uint16_t tone_t0period	6
const uint16_t tone_tbl[]	6
const uint16_t tone_len	6
3. Conclusion	7



1. Introduction

This application note describes how to use the AX5043 for transmitting FM tones as they are used for selective calling (ZVEI and similar schemes).



2. The AX5043_TX_FM_tones_(ZVEI) Project

The MASTER/main.c file of the AX5043_TX_FM_tones_(ZVEI) project demonstrates the transmission of FM tones. Upon pushing button "D" on the DVK-2 mainboard the tones encoding the digits 'A', '5', '0', '4', '3' in the ZVEI scheme are transmitted.

The carrier frequency is 868.3MHz, +/-3kHz FM deviation are used and an 48MHz TCXO is assumed.

The FM tones are generated as follows: The AX5043 is set up transmitting CW. Using a TIMER0 interrupt the frequency register is updated periodically in order to generate the desired tone. This is done for a defined number of sampling points. The procedure can be repeated for generating further tones. Finally the AX5043 is put into power-down mode and the MCU goes into sleep mode.

Note: This project was derived from an AX-RadioLAB project. However, due to the nature of the task, the dependence of the AXRadioV2API has been removed and communication with the AX5043 radio chip is done directly in the code or via LibMF routines. In order to work with this project MASTER/MASTER.cbp should be opened using the AXCode::Blocks IDE.

The files axradiolabstate.xml and AX_Radio_Lab_output/* have been kept. Thus it is still possible to open the project using AX-RadioLAB in order to compute register values when attempting to change parameters. However, the files AX_Radio_Lab_output/* are not used by the code. Changed register values have to be copied manually from AX_Radio_Lab_output/config.c into the init_ax5043() in main.c (see below).

When using the F143-MINI-DVK rather than the DVK-2 it is necessary to comment in the line `///#define MINI_KIT` and to comment out `///#define USE_LCD` at the top of main.c

2.1. Routines

`void init_ax5043(void)`

This routine resets the AX5043, configures the registers necessary for transmit and ranges the PLL for the frequency configured in the FREQA register. In order to change parameters as the carrier frequency, internal vs external VCO, XTAL or TCXO frequency etc. It is easiest to open the project with with AX-RadioLAB, change the corresponding parameters and update the register values in init_ax5043_regs from the values found in



AX_Radio_Lab_output/config.c (the carrier frequency is not assigned to the FREQA register in config.c, but assigned to the axradio_phy_chanfreq variable).

When changing the carrier frequency it is further necessary to update the freq_tbl_sin[][] table (see below).

void send_tone_prepare(void)

This routine powers up the transmitter in CW mode. Further TIMER0 is set up to be clocked at $f_{\text{radio_xtal}} / 2^{\text{tone_rclk_div}}$ and to generate interrupts at $f_s = f_{\text{radio_xtal}} / 2^{\text{tone_rclk_div}} / \text{tone_t0period}$. The frequency f_s is the sampling frequency at which the AX5043 frequency register is updated.

void send_tone(uint8_t n)

This routine sets the frequency of the generated tone by writing the tone_tbl. It further resets tone_sample_cnt, which measures the length of the generated tone in samples. The routine returns after transmitting the tone.

void send_tone_end()

This routine puts the AX5043 into power-down and disables the TIMER0.

void timer0_interrupt(void)

This routine toggles the FREQSEL bit in AX5043_PLLLOOP, which switches between the AX5043_FREQA and AX5043_FREQB registers. It then increments the phase accumulator tone_phase by tone_freq and writes the frequency of the next sampling point to the currently unused frequency register. Further tone_sample_cnt is incremented. This counter measures the length of the tone in samples.

Note: The execution time of the timer0_interrupt ISR is roughly 10us. Modifications of this routine, e.g. in order to get rid of the hard-coded carrier frequency, may increase the execution time and thus require lower f_s . (Increase tone_rclk_div or tone_t0period.)



2.2. Variables

`uint8_t freq_tbl_sin[256][4]`

This array contains the frequency register values sampling one period of the modulation with 256 points, thus

$$f_{carrier} + f_{deviation} \times \sin(2\pi \cdot n / 256) \times \frac{2^{24}}{f_{radio_xtal}}.$$

For each sampling point the 32bit frequency register value is stored as 4 bytes in the order {FREQA0, FREQA1, FREQA2, FREQA3}. Note that the PLL requires that bit 0 of the FREQA0 is always set in order to prevent tonal behaviour of the Sigma-Delta Modulator.

Note that the full frequency is tabulated, not just the deviation from $f_{carrier}$. This avoids 32bit addition on each frequency update, allowing maximum sampling speed. The drawback is the lost flexibility in changing $f_{carrier}$.

The file MASTER/print_tab.c contains a simple routine for computing the above table on the AX8052 MCU and printing it on the DebugLink interface.

`uint8_t tone_rclk_div`

TIMER0 is clocked at $f_{radio_xtal} / 2^{\text{tone_rclk_div}}$

Allowed values are [0, 11].

`uint16_t tone_t0period`

TIMER0 interrupts for updating the frequency register are generated at the sampling frequency $f_s = f_{radio_xtal} / 2^{\text{tone_rclk_div}} / \text{tone_t0period}$.

Higher f_s give higher quality representation of the tones. The default used in the example project is $f_s = 48\text{MHz} / 2^{10} / 1 = 46.875\text{kHz}$, which is on the high side. Note: The execution time of the timer0_interrupt ISR, which handles the frequency adjustment, is roughly 10us. Modifications of that routine, e.g. in order to get rid of the hard-coded carrier frequency, may increase the execution time and thus require lower f_s .

`const uint16_t tone_tbl[]`

This array lists the tone frequencies used. Default is ZVEI. The units are $(f_{\text{tone}}/f_s) \cdot 2^{16}$, where f_s is the sampling frequency.


`const uint16_t tone_len`

This variable defines the tone length in samples.



3. Conclusion

It is possible to transmit analog FM tones as used in various selective calling schemes using the AX5043.

ON Semiconductor and the  are registered trademarks of Semiconductor Components Industries, LLC (SCILLC) or its subsidiaries in the United States and/or other countries. SCILLC owns the rights to a number of patents, trademarks, copyrights, trade secrets, and other intellectual property. A listing of SCILLC's product/patent coverage may be accessed at www.onsemi.com/site/pdf/Patent-Marking.pdf. SCILLC reserves the right to make changes without further notice to any products herein. SCILLC makes no warranty, representation or guarantee regarding the suitability of its products for any particular purpose, nor does SCILLC assume any liability arising out of the application or use of any product or circuit, and specifically disclaims any and all liability, including without limitation special, consequential or incidental damages. "Typical" parameters which may be provided in SCILLC data sheets and/or specifications can and do vary in different applications and actual performance may vary over time. All operating parameters, including "Typicals" must be validated for each customer application by customer's technical experts. SCILLC does not convey any license under its patent rights nor the rights of others. SCILLC products are not designed, intended, or authorized for use as components in systems intended for surgical implant into the body, or other applications intended to support or sustain life, or for any other application in which the failure of the SCILLC product could create a situation where personal injury or death may occur. Should Buyer purchase or use SCILLC products for any such unintended or unauthorized application, Buyer shall indemnify and hold SCILLC and its officers, employees, subsidiaries, affiliates, and distributors harmless against all claims, costs, damages, and expenses, and reasonable attorney fees arising out of, directly or indirectly, any claim of personal injury or death associated with such unintended or unauthorized use, even if such claim alleges that SCILLC was negligent regarding the design or manufacture of the part. SCILLC is an Equal Opportunity/Affirmative Action Employer. This literature is subject to all applicable copyright laws and is not for resale in any manner.

PUBLICATION ORDERING INFORMATION

LITERATURE FULFILLMENT:

Literature Distribution Center for ON Semiconductor
19521 E. 32nd Pkwy, Aurora, Colorado 80011 USA
Phone: 303-675-2175 or 800-344-3860 Toll Free USA/Canada
Fax: 303-675-2176 or 800-344-3867 Toll Free USA/Canada
Email: orderlit@onsemi.com

N. American Technical Support: 800-282-9855 Toll Free
USA/Canada

Europe, Middle East and Africa Technical Support:
Phone: 421 33 790 2910

Japan Customer Focus Center
Phone: 81-3-5817-1050

ON Semiconductor Website: www.onsemi.com

Order Literature: <http://www.onsemi.com/orderlit>

For additional information, please contact your local
Sales Representative